



# Compact Photonic Tools

## Optical Return Loss Meter (cORL-A1)



The Viavi Solutions Compact Photonic Tools offer a new portfolio of point solutions for fiber optic test applications. The cORL-A1 provides a compact, intuitive Optical Return Loss Meter designed to enable applications ranging from simple continuity verification and return loss testing to integration into process automation equipment designed for automated alignment.

The Viavi Compact Photonic Tools offer a new portfolio of point solutions for fiber optic test applications. The cORL-A1 provides a compact, intuitive Optical Return Loss Meter designed to enable applications ranging from simple continuity verification and return loss testing to integration into process automation equipment designed for automated alignment.

Available in two or three laser versions with the option to select from four key wavelengths: 1310, 1490, 1550, and 1625 nm. The integrated multiplexer and single optical output found in the cORL-A1 greatly simplifies the optical connections and calibrations. The 65 dB dynamic range in return loss enables the measurement of high performance angled physical contact (APC) connectors.

A simple intuitive graphical user interface (GUI) and keypad minimizes training requirements. A universal serial bus (USB) interface may be used for test automation interfacing to a PC. While connected by USB, the cORL-A1 does not require an additional mains connection, reducing cord tangle.

### Three Units for the Price of One

The cORL-A1 is actually three units in one. Through the use of the mode key, the unit will operate as a simple fiber-coupled optical power mode (OPM) or as a simple Fabry-Perot Light Source. Full standard commands for programmable instruments (SCPI) for these other modes are supported.

### Key Features

- Provides versatility with optical power, return loss, and light source in single unit
- Operates at four key FTTx wavelengths (1310, 1490, 1550, and 1625 nm)
- Combines two or three laser versions on a single output
- Dynamic range of 65 dB for return loss measurements

### Applications

- Serves as a general purpose lab tool
- Performs return loss testing of FTTx and passive optical components
- Performs return loss testing of optical connectors and cables
- Monitors back reflection during alignment process



## Innovative Features Reduce Test Duration by 3X When Paired with a cOPM-A1

### TWIN or TRIPLE Test

Enabling TWIN or TRIPLE test features on the cOPM-A1 dramatically lowers test durations by allowing simultaneous measurement of two or three wavelengths. Accessing this features requires pairing a cOPM-A1 with the cORL-A1. When this feature is enabled on both units, the cOPM-A1 will automatically detect the wavelengths present and display the simultaneous measured output power (or loss) for each. Additionally, with these two units paired together, simultaneous insertion loss and return loss may be measured. Pairing the cORL with the cOPM created the functionality of the historic Viavi RM Series or singlechannel RX Series.

## Specifications

| Parameter              | cORL-A1                                    |
|------------------------|--|
| <b>ORL Mode</b>        |  |
| Peak wavelength        | 1310, 1490, 1550, 1625 nm                  |
| Wavelength accuracy    | ±20 nm                                     |
| Fiber type             | SMF-28                                     |
| Wavelength settings    | 780 to 1600 nm, step size 1 nm             |
| Spectral width         | <5 nm                                      |
| Return loss range      |  |
| Single wavelength      | 0 to 70 dB                                 |
| Multiwavelength        | 0 to 50 dB                                 |
| Resolution             | 0.01 dB                                    |
| Return loss accuracy   | ±0.7 dB (0 to 50 dB) ±0.9 dB (50 to 60 dB) |
| <b>FPL Mode</b>        |  |
| Maximum output power   | 0 dBm                                      |
| Attenuation range      | 7 dB                                       |
| Attenuation resolution | 0.01 dB                                    |
| Modulation             | CW, 270 Hz, 1 kHz, 2 kHz                   |
| Stability              | ±0.02 dB (15 min)/±0.2 dB (8 hr)           |

| Parameter                                       | cORL-A1  |
|---|--|
| <b>OPM Mode</b>                                 |  |
| Wavelength range                                | 1260 to 1650 nm                                    |
| Power range                                     | -70 to +6 dBm                                      |
| Display resolution                              | 0.01 dB/0.001 μW                                   |
| Fiber type                                      | SMF  |
| Uncertainty at reference condition <sup>1</sup> | ±0.4 dB  |
| <b>General</b>                                  |  |
| Connector type                                  | Interchangeable APC adapters (SC, FC, LC, ST, DIN) |
| Recalibration period                            | 1 year   |
| Warm-up time                                    | 5 min  |
| Operating temperature                           | -10 to +55°C                                       |
| Humidity  | Noncondensing                                      |
| Dimensions (W x H x D)                          | 250 x 88 x 210 mm (9.84 x 3.46 x 8.27 in)          |
| Weight  | 1.8 kg (4 lbs)                                     |
| Remote interface                                | USB (through virtual com port driver)              |
| Powering options                                | Auto-sensing                                       |
| Mains   | 100 to 240 V AC, 50 to 60 Hz                       |
| USB   | Direct from USB, no main required                  |
| Power consumption <sup>2</sup>                  | 1.1 W  |

1. Reference condition: -20 dBm (CW), 1310 ±1 nm, 23 ±3°C, to 75% RH, 9 μm

2. When connected to the AC power plug

## Ordering Information

| Description  | Product Code |
|--|--------------|
| DualWavelength Optical Return Loss Meter – 1310, 1550 nm         | BN 2298/21   |
| TripleWavelength Optical Return Loss Meter – 1310, 1490, 1550 nm | BN 2298/22   |
| TripleWavelength Optical Return Loss Meter – 1310, 1550, 1625 nm | BN 2298/23   |

All versions come with universal APC adapters from BN 215x/00.xx range.



Contact Us **+1 844 GO VIAVI**  
(+1 844 468 4284)

To reach the Viavi office nearest you, visit [viavisolutions.com/contacts](http://viavisolutions.com/contacts).

© 2015 Viavi Solutions, Inc.  
Product specifications and descriptions in this document are subject to change without notice.  
cptorl-ds-lab-tm-ae  
30162504 903 0311