



# VIAVI OSCA-710


First In-Service Pol-Mux Optical Spectrum & Correlation Analyzer.

Characterize and diagnose 40/100/200G, and 400G traffic without shutting down the network or individual channels.

Measuring Optical Signal-to-Noise-Ratio (OSNR) in live Dense Wavelength Division Multiplexing (DWDM) systems using polarization multiplexed transmission (Pol-Mux) is an unsolved challenge. The VIAVI Pol-Mux OSCA-710 is the first instrument to use a novel spectral correlation technique (SCorM, VIAVI patent) to enable the measurement of in-band OSNR, and per channel chromatic dispersion of 40 Gb/s, 100 Gb/s, 200 Gb/s and 400 Gb/s coherent transmission signals utilizing Pol-Mux in a live system, without shutting down the network or individual channels.

The method is independent of modulation format and data rate and

is tolerant of large amounts of chromatic dispersion (CD) and polarization mode dispersion (PMD) as well as spectral filtering in ROADMs. The use of ultra-high resolution coherent receivers



provides complete signal characterization in amplitude, frequency, phase, and polarization to be independent of modulation formats.

The VIAVI SCorM method enables the first ever measurements of inband OSNR in live, coherent systems with Pol-Mux. The OSCA-710 will significantly simplify optical testing during installation, commissioning and maintenance, and minimize overall system downtime and man-hours.

# Configuration: OSCA-710 Kit (Incl. TB/MTS-8000 MF)

**OSCA-710:** Optical spectrum & correlation analyzer module

**UTM-710:** Utility Module (optional) includes optical pre-amplifier for low ch-power applications and optical pre-filter for high channel count applications.



#### **Benefits**

- Industry's first OSCA that measures in-band OSNR on Pol-Mux signals
- First instrument that measures per channel CD
- Characterize traffic without shutting down the network or individual channels

#### **Key features**

- Supports PM-BPSK, PM-QPSK, and PM-xQAM modulation formats
- Tolerant of ROADM filtering and of high CD and PMD
- Ultra-high resolution, coherent OSCA for testing Nyquist- and Super-Channels
- WDM-Expert software for autoidentification of symbol-rate in mixed traffic pipes

### **Applications**

- Core and metro DWDM networks with or without ROADMs
- Undersea communication links
- Qualification of any fiber optic link utilizing coherent detection



# **Specifications (preliminary)**

Technical specifications OSCA-710 (1)					
Spectral					
Wavelength/frequency range	1527.6 – 1565.50 nm /196.25 – 191.50THz				
Abs. wavelength accuracy	±10 pm / ± 1250 MHz				
Resolution bandwidth	< 1 pm / < 100 MHz				
Min channel spacing for signal separation	<8pm / <1 GHz				
Number of optical channels	Up to 256				
Display resolution	0.001 nm / 100 MHz				
Power					
Input power range (per channel) (2)	-40 to +10 dBm				
Max. non-destructive total power	+23 dBm				
Noise floor	<-65 dBm				
Abs. power accuracy (4)	±0.6 dB				
Display resolution	0.01 dB				
OSNR					
OSNR measurement modes	Out-of-band (IEC 61280-2-9), In-band (spectral correlation)				
OSNR measurement range (3)	Up to > 30 dB				
OSNR measurement accuracy (3)	±0.5dB				
Modulation formats	all formats supported incl. DP-xPSK, DP-xQAM and Nyquist shaped signal				
Chromatic dispersion					
Measurement mode	In-service measurement of the chromatic dispersion per channel				
Measurement range	Up to >50.000 ps/nm				
Measurement Modes					
Analysis	In-band OSNR, WDM, Drift, DFB, CD				
Display	Graph, WDM Table, Graph + Table				
UTM-710: Utility Module					
Required for systems with >8 channels and/or channel	el power <-20dBm. Includes optical pre-amplifier and optical pre-filter				
Optical Interfaces					
OSCA-710, UTM-710	SM-APC				
Optical adapters	Interchangeable, type 2150/00.xx FC, SC, ST, DIN				
ORL	>35 dB				
Temperature					
Operating	+0 to +30°C / 32 to 86°F				
Storage	-20 to +60°C /-4 to 140°F				
Dimensions and weight					
OSCA-710 module	39x250x305 mm / 1.5x9.8x12 in 1.8 kg / 4 lbs				
UTM-710 module	39x250x305 mm / 1.5x9.8x12 in 1.8 kg / 4 lbs				

<sup>(1)</sup> Unless otherwise specified, all specifications are based on a temperature of 23°C ±2°C with an FC/APC connector after warm-up

<sup>(4)</sup> For 100Gbit/s modulated signals

Ordering information			
OSCA-710 module UTM-710 module (requires factory upgrade)	2323/91.11 2323/86.11	OSCA-710 Kit (incl. OSCA-710 + UTM-710 + TB/MTS-8000 MF)	2323/93.12

<sup>(3)</sup> Valid for OSNR measurements according IEC 61280-2-9. For in-band OSNR measurements at 100Gps DP-QPSK signals and >-20dBm/ch: OSNR range = 10 to 25 dB, OSNR accuracy = ±1 dB

## **VIAVI Care Support Plans**

#### Increase your productivity for up to 5 years with optional VIAVI Care Support Plans:

- Maximize your time with on-demand training, priority technical application support and rapid service.
- Maintain your equipment for peak performance at a low, predictable cost.

For more Information: go to viavisolutions.com/viavicareplan

Features \*5-year plans only

Plan	Objective	Technical Assistance	Factory Repair	Priority Service	Self-paced Training	5 Year Battery and Bag Coverage	Factory Calibration
BronzeCare	Technician Efficiency	Premium	✓	<b>√</b>	✓		
SilverCare	Maintenance & Measurement Accuracy	Premium	✓	✓	✓	<b>√</b> *	✓



Contact Us

**+1 844 GO VIAVI** (+1 844 468 4284)

To reach the VIAVI office nearest you, visit viavisolutions.com/contacts.

© 2020 VIAVI Solutions Inc. Product specifications and descriptions in this document are subject to change without notice. osca710-ds-fop-tm-ae 30179881 902 0120